
# MDCA Series



## FEATURES

- 
- 
- 
- 
- 
- 
- 
- 

## APPLICATION

- 
- HVAC
- 
- Audio subsystem
- Digital instrument cluster
- 

| Temperature Rise Current Typ. (A) | Current Typ. (A) | DC Resistance Typ. (mΩ) | DC Resistance Max. (mΩ) |
|---|---|---|---|

| Part No | Inductance @ 100KHz/1V (μH) | | | | | |
|---|---|---|---|---|---|---|
| | | | | | | |
| MDCA1040-R22M | | | | | | |
| MDCA1040-R33M | | | | | | |
| MDCA1040-R36M<br>MDCA1040-R47M | | | | | | |
| | | | | | | |
| MDCA1040-R68M | | | | | | |
| MDCA1040-1R0M | | | | | | |
| | | | | | | |
| MDCA1040-2R2M | | | | | | |
| MDCA1040-3R3M | | | | | | |
| MDCA1040-4R7M | | | | | | |
| | | | | | | |
| MDCA1040-6R8M | | | | | | |

| Part No | Inductance @ 100KHz/1V | Tolerance | Temperature Rise Current Typ. (A) | Satura on Current Typ. (A) | DC Resistance Typ. (mΩ) | DC Resistance Max. (mΩ) |
|---|---|---|---|---|---|---|
| MDCA1040-8R2M | | ±20% | | | | |
| MDCA1040-100M | | ±20% | | | | |
| | | ±20% | | | | |
| MDCA1040-220M | | ±20% | | | | |
| MDCA1040-330M | | ±20% | | | | |
| MDCA1040-470M | | ±20% | | | 147 | |

